

Workspace ONE Chrome OS Platform Guide

VMware Workspace ONE UEM 1811



vmware®

You can find the most up-to-date technical documentation on the VMware website at:

<https://docs.vmware.com/>

If you have comments about this documentation, submit your feedback to

docfeedback@vmware.com

VMware, Inc.
3401 Hillview Ave.
Palo Alto, CA 94304
www.vmware.com

Copyright © 2018 VMware, Inc. All rights reserved. [Copyright and trademark information.](#)

Contents

1	Overview	4
	Introduction to Chrome OS Management	4
	Requirements for Deploying Chrome OS	4
	Setup Chrome OS Configuration Settings	5
2	Chrome OS Enrollment	6
	Enroll Chrome OS Devices	6
3	Chrome OS Profiles	8
	Configure Network Profile (Chrome OS)	9
	Configure Sign-In Settings (Chrome OS)	11
	Configure Security & Privacy Profile (Chrome OS)	12
	Configure Kiosk Profile (Chrome OS)	12
	Configure System Updates Profile (Chrome OS)	13
	Configure Content Profile (Chrome OS)	14
	Configure Security & Privacy Profile (Chrome OS)	15
	Configure Time Zone Profile (Chrome OS)	16
	Configure URL Access Controls	16
	Configure Application Control Profile (Chrome OS)	17
	Configure Power Management Profile (Chrome OS)	17
	Configure Printing Profile (Chrome OS)	18
	Use Custom Settings (Chrome OS)	18
4	Chrome OS Management	20
	Device Dashboard	20
	Device List View	21
	Device Management Commands for Chrome OS Devices	22

Overview

This chapter includes the following topics:

- [Introduction to Chrome OS Management](#)
- [Requirements for Deploying Chrome OS](#)
- [Setup Chrome OS Configuration Settings](#)

Introduction to Chrome OS Management

Chrome OS is a Linux-based operating system created and distributed by Google derived from the open-source Chromium OS. Chrome OS is used primarily while connected to the Internet and most files, data, and applications are stored in the cloud.

VMware Workspace ONE UEM™ provides you with a robust set of mobility management solutions for enrolling, securing, configuring, and managing your Chrome OS device deployment.

Requirements for Deploying Chrome OS

Consider the requirements from the AirWatch team before deploying Chrome OS devices. Understanding this information helps prepare you for a successful deployment of devices.

Supported Devices

Refer the Chrome OS website for the most up-to-date list of supported devices.

Chrome Enterprise Licensing

To get started with Chrome OS device management, obtain a Chrome Enterprise license for each device you want to manage. For more information about Chrome Enterprise licensing, contact your Chrome OS device reseller or your Google sales representative.

You can view and manage your Chrome Enterprise licenses from the Google Admin Console.

You must put in a request to use Chrome OS Management through AirWatch and obtain service account details for a successful deployment.

User Setup AirWatch needs access to the same list of users that are present in the Google Admin Console which is facilitated through Directory Integration. For more information on Directory Integration, see the Directory Services Integration Guide. For more information on how to sync users in the Google Admin Console, see the Google Cloud Directory Sync documentation from Google.

Setup Chrome OS Configuration Settings

The setup page from the Workspace ONE Console facilitates the integration between AirWatch and Google for Chrome OS management. Simply enter your Google admin account and you are redirected to Google authorization page to grant permissions.

- 1 Enable Chrome Device Management (CDM) API Partner Access for device and user policies under from the Google Admin Console by navigating to **Device Management > Chrome Management > Device Settings and Device Management > Chrome Management > User Settings** and select the checkbox under the Chrome Management-Partner Access section.
- 2 Navigate to **Devices > Device Settings > Devices & Users > Chrome OS > Chrome OS EMM Registration** in the Workspace ONE console.
- 3 Enter the **Google Admin Email Address**.
- 4 Select **Register with Google**. You are redirected to the Google login page to enter your Google admin email address.

Caution Please make sure you have pop-ups enabled otherwise the Google authorization page will not open.

- 5 Select **Allow** to grant permissions.
- 6 Copy Google Authorization Code from Google and paste it into the **Google Authorization Code** field in the Workspace ONE console.
- 7 Select **Authorize**.
- 8 Select **Test Connection** to ensure the connection between AirWatch and Google is established. If successful, a green 'Test Connection Successful' message displays.
- 9 Select **Device Sync** which manually syncs new Chrome OS enrollments into the Workspace ONE UEM console .

Chrome OS Enrollment

Each Chrome OS device in your organization's deployment must be enrolled before it can communicate with AirWatch and access internal content and features.

Enrolled devices adhere to the Chrome management policies set in the Workspace ONE UEM console until you wipe or recover them. Enrollment occurs during the device setup of the Chrome OS device out of the box. Follow the prompts on the device until you get to the 'Sign into the Chromebook page'. A device has to be enrolled before any user signs in (including an admin). If a user signs in before enrollment, device policies do not apply, and you do not have to wipe the device to restart enrollment.

Device Sync and New Device Enrollment

AirWatch syncs new Chrome device enrollments every 60 minutes. Syncing pulls in a list of all new Chrome OS devices enrolled since the last sync in the device list view. You can use the Device Sync option in the Chrome OS configuration to sync devices into the Workspace ONE UEM console sooner. For more information on the Chrome OS Configuration page, see [Setup Chrome OS Configuration Settings](#)

Enroll Chrome OS Devices

Enrollment is facilitated from the Chrome OS device using the Google admin credentials or existing G Suite user credentials.

To enroll the Chrome OS device:

- 1 Power on the Chromebook and connect to Wi-Fi.
- 2 Press **CTRL+ALT+E** to proceed to enterprise enrollment at the 'Sign into the Chromebook' page. This function bypasses the sign-in screen.
- 3 Enter the user name and password from your Google Admin welcome letter or use your existing G Suite user credentials.
- 4 Enter Device information (Optional).
- 5 Select **Done**. Perform steps 1–5 on all devices that you want to enroll.
- 6 Navigate to **Devices > Device Settings > Devices & Users > Chrome OS > Configuration**.

- 7 Select **Device Sync** which syncs all new enrollments into the Workspace ONE UEM console . If you do not select Device Sync, new enrollments are automatically synced every 60 minutes.

After you select done, the Chromebook automatically applies any pre-configured device policies and is ready for a user to sign in. Once a user signs in, all applicable user profiles are pushed to the Chrome device. For more information, see [Chapter 3 Chrome OS Profiles](#). Once devices are enrolled, they display in the Device List View in the Workspace ONE UEM console .

Chrome OS Profiles

Profiles serve many different purposes from letting you enforce rules and procedures to tailoring and preparing Chrome OS devices for how they are used with AirWatch.

The individual settings you configure, such as restrictions and bookmarks, are called payloads. In most cases, Consider configuring one payload per profile, which means you have multiple profiles for the different settings you want to push to devices. For example, you can create a profile to restrict users from using incognito mode.

Important When applying profiles across parent and child organization groups, the device accepts the latest profile pushed to the device not the most restrictive like other platforms. Do not apply the same payload in both a parent and child organization group to the same device.

Device Profiles

Device policies apply to Chrome OS devices regardless of any user logged into the device. Device policies are applied through Smart Groups.

Smart groups are customizable groups that determine which platforms, devices, and users receive an assigned application, book, compliance policy, device profile, or provision.

User Profiles

User policies for Chrome OS allow you to configure profile settings at the user level. The policies do not apply to users signed in as guest or with a Google Account outside of your organization (such as a personal Gmail account). You are able to view **User Details** by selecting the user icon under the **Installed Status** field.

User policies are applied through User Groups. User groups are sets of users into user groups which, like organization groups, act as filters for assigning profiles and applications.

Profiles

- Profiles do not have an add version option. If the profile is edited and saved, the updated policy is sent to devices.

- Profiles for Chrome OS are deployed using API calls, which are a different solution than is used with other platforms, in which the profile is sent directly to the Workspace ONE Intelligent Hub on the device. For Chrome OS devices, the Workspace ONE UEM console relies on API responses to the Google Cloud to push new policies. The Console displays a green check mark to show that the policy has been updated to the Google cloud.
- Profiles do not show a 'Publish Preview'. When you select Save & Publish, the profile takes effect immediately.
- All user and device profile information, including certificates, are sent to Google and stored by Google

Application Management

- Chrome apps are pushed through profiles using the Application Control profile, not through Apps & Books.

This chapter includes the following topics:

- [Configure Network Profile \(Chrome OS\)](#)
- [Configure Sign-In Settings \(Chrome OS\)](#)
- [Configure Security & Privacy Profile \(Chrome OS\)](#)
- [Configure Kiosk Profile \(Chrome OS\)](#)
- [Configure System Updates Profile \(Chrome OS\)](#)
- [Configure Content Profile \(Chrome OS\)](#)
- [Configure Security & Privacy Profile \(Chrome OS\)](#)
- [Configure Time Zone Profile \(Chrome OS\)](#)
- [Configure URL Access Controls](#)
- [Configure Application Control Profile \(Chrome OS\)](#)
- [Configure Power Management Profile \(Chrome OS\)](#)
- [Configure Printing Profile \(Chrome OS\)](#)
- [Use Custom Settings \(Chrome OS\)](#)

Configure Network Profile (Chrome OS)

The Network profile allows you to configure network connection settings to apply towards device policies and user policies.

To configure the Network profile:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **Device** to deploy settings to the device profile. Select **User** to deploy settings to the user profile.

- 3 Configure the **General** profile settings as appropriate. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Network** payload.
- 5 Configure **Wi-Fi** settings, including:

Setting	Description
Wi-Fi	
Service Set Identifier	Provide the name of the network the device connects to.
Connectivity	Indicate if the Wi-Fi network is Hidden or Auto-Join . Auto-Join indicates that the network is connected automatically when in range.
Security Type	Specify the access protocol used and whether certificates are required. If WPA/WPA2 is selected, the Password field displays. If WPA/WPA2 Enterprise is selected, the following fields display: <ul style="list-style-type: none"> ■ Extensible Authentication Protocol (EAP) - Specify the EAP from the drop-down menu. ■ Identity - Enter a description to which is used to identify the certificate during authentication. ■ Root Certificate - Use the Certificates section at the bottom to add the Root Certificate. ■ Client Certificate - Use the Certificates section at the bottom to add the Client Certificate.
Password	Provide the password for the device to connect to the network. The password field displays when WPA/WPA 2 is selected from the Security Type field.
Proxy	Enter the proxy details.
Gateway Platform	Describes the gateway address to use for the configuration. Select the gateway as Direct Internet Connection , Manual Proxy Configuration , or Automatic Proxy Configuration to configure settings.
HTTP Proxy Host	Enter the host name of IP address for the proxy server. This field displays if Manual Proxy Configuration is selected.
HTTP Proxy Port	Enter the target port for the proxy server. This field displays when Manual Proxy Configuration is selected.
Secure HTTP Proxy Host	Enter settings for the secure HTTP proxy. This field displays when Manual Proxy Configuration is selected.
Secure HTTP Proxy Port	Enter secure port to use for proxy. This field displays when Manual Proxy Configuration is selected.
FTP Proxy Host	Enter the host name of IP address for the FTP proxy server. This field displays when Manual Proxy Configuration is selected.
FTP Proxy Port	Enter the target port for the FTP proxy server. This field displays when Manual Proxy Configuration is selected.
SOCKS Host	Enter the settings host address for the SOCKS proxy. This field displays when Manual Proxy Configuration is selected.
SOCKS Port	Enter the target port for the SOCKS proxy server. This field displays when Manual Proxy Configuration is selected.

Setting	Description
No Proxy for the following Domains (Comma-Separated domains)	Enter the domains whose traffic is not handled by the proxy settings. This field displays when Manual Proxy Configuration is selected.
Autoconfiguration URL (Leave blank for WPAD protocol)	Enter the URL which defines how web browsers and other user agents can automatically choose the appropriate proxy server (access method). This field displays when Automatic Proxy Configuration is selected.
Certificate	
Add Certificate	Select whether to Upload certificate file or Select certificate template . When you select Upload Certificate, you are directed to a dialog to upload your certificated from your saved files.
Certificate Authority	Select the Certificate Authority and the certificate template from the drop-down menu for your organization group. The certificate authorities and the templates are added for an organization group at Devices > Certificates > Certificate Authorities. This field displays if you choose Select certificate template from the Add Certificate field .
Certificate Template	Select your certificate template and select Add . This field displays if you choose Select certificate template from the Add Certificate field .
File-Upload Field	Select Select File to upload your saved certificate.
Password	Specify a password if the file is protected. Select Add . You will the certificated listed in the Added Certificates section.

6 Select **Save & Publish**.

Configure Sign-In Settings (Chrome OS)

The Sign-in settings profile allows you to restrict access to the device for only a set of users.

To configure the sign-in settings profile:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **Device** to deploy to device policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Sign-In Settings** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
Restrictions	
Restrict Sign-In	Enable to restrict access to the device for only a set of users. When enabled, a text box displays and you can enter a comma-separated list of user names that can sign in to the device. Wildcards(*) can be used, for example, *@example.com .
Guest Mode	Enable to allow guest access to the Chrome browser. A user is not required to sign in.

Setting	Description
User Experience	
Autocomplete Domain	Set the domain name used for autocomplete on the sign-in page. The user can override this domain, if needed.
Single Sign On	
SSO Idp Redirection	Enable to redirect users to a SAML SSO IDP for login to the device.
SAML SSO cookie transfer into user session	Enable to transfer SAML SSO cookies to user session. This setting allows end users to use single sign-on with their apps by simply signing into the Chrome OS device.

6 Select **Save and Publish**.

Configure Security & Privacy Profile (Chrome OS)

The Security and Privacy profile allows you to configure user data settings.

To configure security and privacy settings:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **Device** to deploy to device policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Security & Privacy** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
Clear user data on log out	When enabled, all local user data is cleared from the device when the user logs out. Consider using this setting for shared device use cases.
Force Re-enrollment	Force re-enrollment in the event a device is reset or wiped. After a device is reset, the enrollment screen displays and the user has to re-enroll the device. Select Do not force re-enrollment or Force the device to re-enroll into the previous domain .
Device Verified Mode Required	When enabled, verified boot mode is required for device verification to succeed.

Configure Kiosk Profile (Chrome OS)

The Kiosk profile allows you to lock the device into a single app until the policy is removed.

To configure the Kiosk mode profile:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **Device** to deploy to device policy profiles.

- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Kiosk** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
Kiosk	
Application Name	Enter Application Name for corresponding application ID.
Application Identifier	Enter the application identifier. Find the desired app in the Chrome Web Store and copy the ID from the URL which includes everything after the last forward slash.
Auto Login Bailout	Enable users to press the keyboard shortcut (Ctrl+Alt+S) to prevent auto start of the app at device start-up. By default, the user has 3 seconds to press a shortcut to prevent auto-launch.
Prompt for Network Offline	<p>Enable to display network configuration prompt when the device cannot connect to the network.</p> <p>Important If both Prompts for Network Offline and Auto Login Bailout settings are disabled, the device might become unusable when there is no Internet access and has to go through the recovery process. If the device is offline at start-up, the network configuration screen always displays, before auto-launch.</p>
Extension Policy	Enable to configure applications with JSON. Refer to the app developer's documentation for the format expected by the app.
System Log Upload (Every 12 Hours)	Enable to send system logs to the Chrome Admin Console in 12-hour increments.
Monitor Online/Offline Status	Enable to receive alerts if the device is online or offline.
Device Status Alerts	
Send Email if Device is Offline	Enable and enter email address with comma separation if more than one. Use this setting if Monitor Online/Offline Status is enabled.
Send SMS if Device is offline	Enable and enter the phone number with comma separation if more than one.

- 6 Select **Save and Publish**.

Configure System Updates Profile(Chrome OS)

The System Updates profile specifies whether Chrome device updates automatically update to new versions of Chrome as they are released.

To configure system updates settings:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **Device** to deploy to device policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **System Updates** profile and select **Configure**.

5 Configure the following settings as desired for your organization:

Setting	Description
Allow Auto Update	Enable to allow device to automatically update to the latest version when available.
Allow Kiosk App to Control Target Platform Version	Enable to allow the kiosk application to set the target platform version through an extension policy.
Target Platform Version	Specify the prefix of the target version you want the device to update to if the device is on an older version. If the device is already on a version with the given prefix, then there is no effect. If the device is on a higher version, it remains on the higher version.
Maximum Update Delay Duration (hours)	Specify a duration (up to 14 days) during which your devices randomly receive system updates to ensure that all devices are not using the bandwidth at a given time.
Reboot After Update	Enable to require automatic reboot the device after it is updated.

6 Select **Save and Publish**.

Configure Content Profile (Chrome OS)

The Content profile allows you to push a list of bookmarks for user convenience that applies to Chrome on all platforms.

To configure content settings:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **User** to deploy to user policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Content** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
Bookmark Bar	Specify whether User can show/hide the bookmarks bar, Always show the bookmarks bar, Never show the bookmarks bar .
Editing Bookmarks	Enable to allow users to edit bookmarks. If this option is disabled, existing bookmarks are still available, but new bookmarks cannot be added. Users will not be able to edit or delete current bookmarks.
Managed Bookmarks	Enable to create a list of bookmarks to be pushed onto Chrome OS.
Home Button	Specify whether User can show/hide the Home button, Always show the Home button, Never show the Home button .
Home Page	Specify whether Allow user to configure, Home page is the new Tab page, Set home page .
Folder Name	Create a hierarchical folder structure of bookmarks.
URL	Enter bookmark URL.

Setting	Description
Name	Enter name to be displayed on the UI.
Pop-Up Configuration	Enable to allow pop-ups and configure user settings.
Pop-Ups	Use the drop-down to configure if pop-ups are to be: Allow user to control pop-up behavior, Allow all sites to show pop-ups, do not allow any sites to show pop-ups.
Sites that can always show pop-ups	Enter URLs to be whitelisted from pop-ups
Sites that are never allowed to show pop-ups	Enter URLs to be blacklisted from pop-ups.
URLs to Open at Startup	Enable to configure a list of websites to launch at start up. When enabled, the URL field displays to enter the URLs.
URL	Enter URLs that will launch on start up. Select Add URL to add multiple.

6 Select **Save and Publish**.

Configure Security & Privacy Profile (Chrome OS)

The Security & Profile allows you to configure incognito settings for the users.

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**
- 2 Select **User** to deploy to user policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Security & Privacy** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
Allow Incognito Mode	Allow users to browse the web without storing local data.
Safe Browsing	Specify whether or not Safe Browsing is turned on for users.
Users can proceed to Malicious Sites	Configure whether or not users can navigate to a potentially malicious site from a warning page.
Saving Browser History	Disables saving browser history in Google Chrome and prevents user from changing this setting. This setting also disables tab syncing which lets you access these web pages on your computer or other synced devices.
Deleting Browser History	Disables deleting browser and download history.
User Verified Mode Required	When enabled, verified boot mode is required for device verification to succeed.

6 Select **Save and Publish**.

Configure Time Zone Profile (Chrome OS)

The Time Zone profile determines automatic timezone selection.

To configure the Time Zone profile:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **Device** to deploy to device policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Time Zone** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
Kiosk	
Automatic Time Zone Detection	<p>Select the type of automatic timezone detection: Let the user decide, Never auto-detect time zone, Use IP to determine location for time zone, Use Wi-Fi access points to determine location for time zone, Use all location information to determine time zone.</p> <p>If this policy is not configured, users can control automatic timezone detection using controls in Chrome settings.</p>

- 6 Select **Save and Publish**.

Configure URL Access Controls

The URL Access controls profile allows you to blacklist certain URLs unless exceptions are configured.

To configure URL access controls:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **User** to deploy to user policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **URL Access Controls** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
URL Blacklist	Prevents the Chrome Browser from accessing certain URLs. Select the Add button to add multiple URLs.
Exceptions	Specifies exceptions to the URL blacklist. Select the Add button to add multiple URLs.

- 6 Select **Save and Publish**.

Configure Application Control Profile (Chrome OS)

The Application Control profile allows you to add apps from the Google Play Store and Chrome Webstore.

To add apps using the application Control profile:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **User** which deploys user policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Application Control** profile and select **Configure**.
- 5 Configure the following settings as desired for your organization:

Setting	Description
Auto Install Android Apps using App Identifier	
Chrome App Access	Use the dropdown to select All Chrome apps are accessible, Only Chrome added below are accessible , or Create a list of blocked Chrome apps .
App ID	The application identifier found in the Google Play Store.
Name	The application display name.
Pin App to Shelf (Y/N)	Enter Y to pin the app to the homescreen dock.
Auto Install Chrome Apps using App Identifier	
App ID	The application identifier found in the Chrome Web Store.
Name	The application display name.
Pin App to Shelf (Y/N)	Enter Y to pin the app to the homescreen dock.
Users can end processes in Task Manager	Enable to allow end user to see the end process option in Chrome OS.

- 6 Select **Save and Publish**.

Configure Power Management Profile (Chrome OS)

The Power Management profile allows you to configure incognito settings for the users.

To configure power management settings:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **User** to deploy to user policy profiles.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Power Management** profile and select **Configure**.

- Configure the following settings as desired for your organization. These settings can be applied whether connected to power or running on battery:

Setting	Description
Idle time after which action is taken (in minutes)	Specify the idle time in minutes before the user's device goes to sleep or signs them out
Action when Idle time is reached	Set whether the device goes into sleep mode, log out, shutdown, or do nothing.
Idle time after which warning is shown to user (in minutes)	Specify the length of time without user input before warning message is displayed.
Idle time after which screen is dimmed (in minutes)	Specify the length of time without user input before screen is dimmed.
Idle time after which screen is turned off (in minutes)	Specify the length of time without user input before screen is turned off.

- Select **Save and Publish**.

Configure Printing Profile (Chrome OS)

The Printing profile enables printing options in Chrome OS. You can choose either to allow using the print preview with Google cloud print or select always use system print dialog window.

To configure printing options:

- Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- Select **User** to deploy to user policy profiles.
- Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- Select the **Printing** profile and select **Configure**.
- Configure the following settings as desired for your organization. These settings can be applied whether connected to power or running on battery:

Setting	Description
Printing	<p>Enable to allow printing from Chrome OS.</p> <p>When disabled, printing is only possible through plug ins that bypass Google Chrome. For example, certain Flash applications that have the print option in their context menu.</p>

- Select **Save and Publish**.

Use Custom Settings (Chrome OS)

The **Custom Settings** payload can be used when new Chrome OS functionality releases or features that AirWatch does not currently support through its native payloads. With the **Custom Settings** payload, enter custom XML code to manually enable or disable certain settings.

To configure custom settings:

- 1 Navigate to **Devices > Profiles & Resources > Profiles > Add > Add Profile > Chrome OS**.
- 2 Select **Device** or **User**.
- 3 Configure the profile's **General** settings. These General profile settings determine how the profile deploys and who receives it.
- 4 Select the **Custom Settings** payload and select **Configure**. Enter the custom XML in the text box. The XML code you paste will contain the complete block of code, from <characteristic> to </characteristic>.
- 5 Select **Save & Publish**.

Chrome OS Management

After your devices are enrolled and configured, manage the devices using the Workspace ONE™ UEM console. The management tools and functions enable you to keep an eye on your devices and remotely perform administrative functions.

You can manage all your devices from the UEM console. The Dashboard is a searchable, customizable view that you can use to filter and find specific devices. This feature makes it easier to perform administrative functions on a particular set of devices. The Device List View displays all the devices currently enrolled in your Workspace ONE UEM environment and their status. The **Device Details** page provides device-specific information such as profiles, apps, Workspace ONE Intelligent Hub version and which version of any applicable OEM service currently installed on the device. You can also perform remote actions on the device from the Device Details page that are platform-specific.

This chapter includes the following topics:

- [Device Dashboard](#)
- [Device List View](#)
- [Device Management Commands for Chrome OS Devices](#)

Device Dashboard

As devices are enrolled, you can manage them from the Workspace ONE UEM **Device Dashboard**.

The **Device Dashboard** provides a high-level view of your entire fleet and allows you to act on individual devices quickly.

You can view graphical representations of relevant device information for your fleet, such as device ownership type, compliance statistics, and platform and OS breakdowns. You can access each set of devices in the presented categories by selecting any of the available data views from the **Device Dashboard**.

From the **List View**, you can take administrative action: send messages, lock devices, delete devices, and change groups associated with the device.

- **Security** – View the top causes of security issues in your device fleet. Selecting any of the doughnut charts displays a filtered **Device List** view comprised of devices affected by the selected security issue. If supported by the platform, you can configure a compliance policy to act on these devices.
 - **Compromised** – The number and percentage of compromised devices (jailbroken or rooted) in your deployment.

- **No Passcode** – The number and percentage of devices without a passcode configured for security.
- **No Encryption** – The number and percentage of devices that are not encrypted for security. This reported figure excludes Android SD Card encryption. Only those Android devices lacking disc encryption are reported in the donut graph.

Ownership – View the total number of devices in each ownership category. Selecting any of the bar graph segments displays a filtered **Device List** view comprised of devices affected by the selected ownership type.

- **Last Seen Overview/Breakdown** – View the number and percentage of devices that have recently communicated with the Workspace ONE UEM MDM server. For example, if several devices have not been seen in over 30 days, select the corresponding bar graph to display only those devices. You can then select all these filtered devices and send them a message requesting that they check in.
- **Platforms** – View the total number of devices in each device platform category. Selecting any of the graphs displays a filtered **Device List** view comprised of devices under the selected platform.
- **Enrollment** – View the total number of devices in each enrollment category. Selecting any of the graphs displays a filtered **Device List** view comprised of devices with the selected enrollment status.
- **Operating System Breakdown** – View devices in your fleet based on operating system. There are separate charts for Apple iOS, Android, Windows Phone, and Windows Rugged. Selecting any of the graphs displays a filtered **Device List** view comprised of devices running the selected OS version.

Device List View

Use the UEM console's Device List View to see a full listing of all devices in the currently selected organization group.

The **Last Seen** column displays an indicator showing the number of minutes elapsed since the device has checked-in. The indicator is red or green, depending on the number of minutes defined in **Device Inactivity Timeout (min)**. This indicator can be set by navigating to **Groups & Settings > All Settings > Devices & Users > General > Advanced**.

Select a device in the **General Info** column at any time to open the details page for that device.

Sort by columns and configure information filters to review device activity based on specific information. For example, sort by the **Compliance Status** column to view only devices that are currently out-of-compliance and target only those devices. Search all devices for a friendly name or user name to isolate one device or user.

Customize Device List View Layout

Display the full listing of visible columns in the **Device List** view by selecting the **Layout** button and select the **Custom** option. This view enables you to display or hide Device List columns per your preferences.

There is also an option to apply your customized column view to all administrators. For instance, you can hide 'Asset Number' from the **Device List** views of the current OG and of all the OGs underneath.

Once all your customizations are complete, select the **Accept** button to save your column preferences and apply this new column view. You can return to the **Layout** button settings at any time to tweak your column display preferences.

Search in Device List View

You can search for a single device for quick access to its information and take remote action on the device.

To run a search, navigate to **Devices > List View**, select the **Search List** bar and enter a user name, device friendly name, or other device-identifying element. This action initiates a search across all devices, using your search parameter, within the current organization group and all child groups.

Device Management Commands for Chrome OS Devices

The **More drop down** on the Device Details page enables you to perform remote actions over-the-air to the selected device. The actions listed vary depending on factors such as device platform, Workspace ONE UEM console settings, and enrollment status.

- **Enterprise Wipe** – Enterprise Wipe a device to unenroll and remove all managed enterprise resources including applications and profiles. This action cannot be undone and re-enrollment is required for VMware AirWatch to manage this device again.